

120V-347V input 0-10V Dimmable Driver for
Lotus LED Lights models LD6R-HO & LD8R-HO



Project: _____

Location: _____

Qty: _____

Notes: _____

DESCRIPTION

120-347V Input Driver 0-10V Dimmable for Lotus LED Lights model models LD6R-HO & LD8R-HO
Output 30-38 V DC, Constant Current 720 mA, PF > 0.95
Connection box wire capacity: Maximum of 5 No 12 AWG or 8 No 14 AWG

DIMENSIONS: 5" x 3 1/2" x 1 1/2"



COMPATIBLE FIXTURES

LD6R-HO
LD8R-HO

CABLE CONNECTORS

2 knock-outs 7/8"

MOUNTING

directly on joist

ORDERING GUIDE

cat # **LLL-LD3580TR**

Input: White (Neutral) & Black (Hot) wires with quick connectors. Connect to 120V - 347V AC according to the Dimmer Manufacturer's Instructions.

Output: Armored FT6 / CMP rated cable with screw-in connector. Connect to compatible Lotus LED fixture from the list above

0-10V control wires: Grey (-) and Purple (+). Connect to dimming or control system 0-10V only. **DO NOT CONNECT TO LINE VOLTAGE.**

If you short the Grey and Purple wires the fixture would be dimmed to zero.

Warning: This driver is UL / cUL certified to be used only with Lotus LED Lights fixtures.

Connecting it to any other manufacturer's fixtures will void certification and warranty and may cause overheating and fire.